

## OL 20/20n – Level 1 Menu List

- To enter the MENU set-up, please ensure the printer is off-line and then briefly depress the MENU button.
- To enter level 2, please ensure the printer is off-line and then hold the MENU button for 2 seconds.
- Move through the MENU button and when you wish to change an option press ENTER and then the **+** or **-** or the **<** **>** keys. Press Enter to set.
- When you have finished with the MENU set-up press ONLINE to save and return to printing mode.

<b>Printer Language</b>	Emulation	HP LaserJet 5, Epson FX, IBM PPR III XL, Adobe PostScript, <b>Auto</b>
<b>Tray Select</b>	Manual	<b>Off</b> ,
	Paper In	<b>Tray 1</b> , Tray 2 ( if installed)
	Auto Tray ( if tray 2 installed)	<b>Off</b> , On
<b>Duplex Printing</b>	Duplex	<b>Off</b>
<b>Edit size</b>	Edit size	<b>Cassette Size</b>
<b>Paper size</b>	Front / Manual	<b>A4</b> , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
<b>Media Type</b>	Tray 1	<b>Medium</b> , M Heavy, Heavy, Light, M Light.
	Tray 2	<b>Medium</b>
	Front / Manual	<b>Medium</b> , M Heavy, Heavy, Light, M Light.
<b>Paper Size Check</b>	Size Check	<b>Enable</b> , Disable
<b>Copies</b>	Copies	<b>1</b> to 99
<b>Fonts and Symbols</b>	Font Source	<b>Resident</b> , Card,( if installed)
	Font No.	<b>1000</b> to 1047
	Font Pitch	<b>10.00CPI</b>
	Symbol (Symbol set)	<b>PC-8</b> , PC-850, IBM-437, IBM-850 Plus many others.
<b>Page Layout 1</b>	A4 Width	<b>78</b> col., 80 col.
	Blnskp (Blank skip)	<b>Off</b>
	CR Function	<b>CR</b> , CR+LF
	LF Function	<b>LF</b> , LF+CR
<b>Page Layout 2</b>	Orientation	<b>Portrait</b>
	Lines per Page	<b>64 Lines</b>
<b>Host Interface</b>	Parallel	<b>Enable</b>
	RS232C	<b>Enable</b>
	OKI HSP	<b>Enable</b>

## Level -2 Menu List

<b>Print Mode</b>	Mode (resolution)	<b>600</b> , V1200 (600x1200), 300
<b>Memory Usage</b>	Font Protection	<b>Auto</b> , Off, 100Kb to 1.1MB
<b>Auto Operation</b>	Auto Continue	<b>Off</b> , On
	Wait Timeout	<b>90</b>
	Manual Timeout	<b>60</b>
<b>Darkness Control</b>	Darkness	<b>0</b> , -1.
<b>Power Saving</b>	Pwr Save	<b>0 Sec</b> , 8 Min, Disable
<b>Low Toner</b>	Low Toner	<b>On</b> , Off
<b>Toner Saving</b>	Toner	<b>Disable</b> , Medium, Light
<b>Clearable Warnings</b>	Clearable Warnings	<b>On</b>
<b>Error Report</b>	Error Report	<b>Off</b>
<b>Parallel I/F</b>	Speed	<b>High</b> , Medium
	BI-Direct	<b>Enable</b> , Disable
	I-Prime	<b>Off</b> , On
<b>RS232C Serial</b>	Flow Control	<b>DTR HI Polarity</b>
	Baud Rate	<b>9600 Baud</b>
	Data Bits	<b>8 Bits</b>
	Parity	<b>None</b>
	Min. Busy Time	<b>200ms</b>
<b>Language</b>	Language	<b>English</b> , German, French, Italian, plus others.