

ML 380

Error Condition	LED Light besides Power and Select						
	Courier	Orator	Helvetica	10 cpi	15 cpi	20 cpi	
Memory Error	On	-	-	On	-	-	MPU RAM error
	-	On	-	On	-	-	Program ROM error
	-	On	-	-	On	-	Resident CG ROM error
	-	On	-	-	-	On	EEPROM error
	-	-	On	On	-	-	External RAM error
	-	On	On	On	-	-	Resident CG error
	-	-	On	-	On	On	RAM Card error
Font Card error	-	On	-	-	On	On	Font Card error
	-	On	On	-	On	On	Font Card release
Spacing Error	On	On	-	On	-	-	Head Homing Error
	On	On	-	-	-	On	Spacing Error
Printhead Error	On	On	-	-	On	-	Thermistor error
Serial I./F Error	On	-	-	-	-	On	