

# ML 520-1

- To enter the MENU set-up ensure the Select light is not on and press the SHIFT & MENU button.
- To move through the menu use the GROUP, ITEM and SET buttons.
- When you have finished with the MENU set-up press SHIFT & MENU to save and return to printing mode.

GROUP	ITEM	SET
<b>PRINTER CONTROL</b>	Emulation Mode	<b>IBM PPR, EPSON FX, OKI ML</b>
<b>FONT</b>	Print Mode	<b>Utility, NQL Courier, NQL Gothic, HSD</b>
	Pitch	<b>10, 12, 15, 17.1, 20, CPI</b>
	Proportional Spacing	<b>No, Yes</b>
	Style	<b>Normal, Italics</b>
	Size	<b>Single, Double</b>
<b>SET-UP</b>	Graphics Printing	<b>Unidirectional, Bi-directional</b>
	7 of 8 Bit Graphics	<b>8, 7</b>
	Max Receive Buffer	<b>64K, 1-Line, 32K</b>
	Paper Out Override	<b>No, Yes.</b>
	Print Registration	<b>0, 0.05, 0.1, 0.15, 0.5, 0.25 mm Left, 0.25, 0.2, 0.15, 0.1, 0.05 mm Right</b>
	Operator Panel Functions	<b>Full Operation, Limited Operation</b>
	Reset Inhibit	<b>No, Yes</b>
	Print Suppress Effective	<b>Yes, No</b>
	Auto LF	<b>No, Yes</b>
	Auto CR (IBM)	<b>No, Yes</b>
	Print DEL Code (ML Mode)	<b>No, Yes</b>
	CSF Bin Select	<b>Bin 1, Bin 2.</b>
	SI Select Pitch (10CPI)	<b>17.1, 15</b>
	SI Select Pitch (12 CPI)	<b>20, 12</b>
	Time Out Print	<b>Valid, Invalid</b>
Printhead Gap Adjust	<b>0, +1, -1</b>	
<b>REAR, BOTTOM &amp; TOP FEED</b>	Line Spacing	<b>6 LPI, 8LPI</b>
	Form Tear Off (With Roll Paper Stand on Top Feed)	<b>Off, 500MS, 1 Sec, 2 Sec</b>
	Skip Over Perforation	<b>No, Yes</b>
	Page Width (ML521 Only)	<b>13.6 “, 8 “</b>
	Page Length	<b>12 “ (Rear &amp; Bottom Feed), 11-2/3 “ (Top Feed), 11”, 14”, 16.57”, 3”, 3.5”, 4”, 5.5”, 6”, 7”, 8”, 8.5”</b>
	Gap Control	<b>Auto Gap, Semi Auto Gap, 1, 2, 3, 4, 5, 6, 7, 8, 9</b>
	Wait Time ( Top Feed Only)	<b>1 sec, 500ms, 2 sec</b>
<b>SYMBOL SETS</b>	Character Set	<b>Set II, Set I</b>
	Code Page	<b>USA, Canada-French, Multilingual, Portugal, Norway, Turkey, Greek 437, 851, 928, Cyrillic, Polska, PC Latin 2, Serbo Croatic I, II, ECMA 94</b>
	Language Set	<b>ASCII, French, German, British, Danish I, Swedish I, Italian, Spanish I, Japanese, Norwegian, Danish II, Spanish II, Latin American, French Canadian, Dutch TRS80, Swedish II, III, IV, Turkish, Swiss I, II, Publisher</b>
	Zero Character	<b>Unslashed, Slashed</b>
	Slashed Letter O	<b>No, Yes</b>
<b>PARALEL OPTIONS</b>	I-Prime	<b>Buffer Print. Buffer Clear, Invalid</b>
	Pin 18	<b>+5V, Open</b>
	AutoFeed XT (Epson mode)	<b>Invalid, Valid</b>
<b>SERIAL INTERFACE OPTIONS</b>	Parity	<b>None, Odd, Even</b>
	Serial Data No. of Bits	<b>8, 7</b>
	Protocol	<b>Ready/Busy, XON/OFF</b>
	Diagnostic Test	<b>No, Yes</b>
	Busy Line	<b>SSD-, SSD+, DTR, RTS</b>
	Baud Rate	<b>9600, 4800, 2400, 1200, 600, 300, 19200, BPS</b>
	DSR Signal	<b>Valid, Invalid</b>
	DTR Signal	<b>Ready On Power Up, Ready On Select</b>
Busy Time	<b>200MS, 1 Second</b>	