

OL 10I – Level 1 Menu List

- To enter the MENU set-up, please ensure the printer is off-line and then briefly depress the MENU button.
- To enter level 2, please ensure the printer is off-line and then hold the MENU button for 2 seconds.
- Move through the MENU button and when you wish to change an option press ENTER and then the **+** or **-** or the **<** **>** keys
- When you have finished with the MENU set-up press ONLINE to save and return to printing mode.

Printer Language	Emulation	HP4, Epson FX, IBM PPR, Hiper-W, Auto
Tray Select	Manual	Off ,
	Paper In	Tray 1 , Tray 2 (if installed)
	Auto Tray (if tray 2 installed)	Off , On
Edit size	Edt size	Cassette Size
Paper size	Tray	A4 , A5, A6, B5, Letter, Exec, Legal 14, Legal 13 (optional tray fitted)
	Manual	A4 , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
	Tray 2 (if installed)	A4 , A5, A6, B5, Letter, Exec, Legal 14, Legal 13
	Feeder (if installed)	A4 , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
Media Type	Tray 1	Medium , M Heavy, Heavy, Light, M Light.
	Manual	Medium , M Heavy, Heavy, Light, M Light.
Paper Size Check	Size Chk	Enable , Disable
Copies	Copies	1 to 99
Fonts and Symbols	Font Source	Resident , Card,(if installed)
	Font No.	1000 to 1047
	Font CPI (if scaleable)	10.00 , 0.44to 99.99
	Font HGT(if scaleable)	12.00 , 4.00 to 999.75
	Symbol (Symbol set)	PC-8 , PC-850, IBM-437, IBM-850 Plus many others.
Page Layout 1	A4 Width	78 col., 80 col.
	Blnsksp (Blankskip)	Off
	CR Function	CR , CR+LF
	LF Function	LF , LF+CR
Page Layout 2	Orientation	Portrait
	Lines per Page	64 Lines
Host Interface	Parallel	Enable
	Network	Enable

Level -2 Menu List

Print Mode	Mode (resolution)	600 , V1200 (600x1200), 300
Memory Usage	RST Buffer	Auto , 480kb to 1.44 Mb
	Font Protection	Auto , Off, 100Kb to 1.1MB
Auto Operation	Auto Continue	Off , On
	Wait Timeout	90
	Manual Timeout	60 , 30
	Print Protection	Good , Better
Darkness Control	Darkness	0 , +1, +2, -2, -1.
Power Saving	Pwr Save	0 Sec , 8 Min, Disable
Low Toner	Low Toner	On , Off
Toner Saving	Toner	Disable , Medium, Light
Clearable Warnings	Clearable Warnings	On
Error Report	Error Report	Off
Parallel I/F	Speed	High , Medium
	BI-Direct	Enable , Disable
	I-Prime	Off , On
Language	Language	English , German, French, Italian, plus others.