

1200ex – Level - 1 Menu List

- To enter the MENU set-up please ensure the printer is off-line and then briefly depress the MENU button.
- To enter level 2 ensure please ensure the printer is off-line and then hold the MENU button for 2 seconds.
- Move through the MENU button and when your wish to change an option press ENTER and then the **+** or **-** or the **<** **>** keys. Press Enter to set.
- When you have finished with the MENU set-up press ONLINE to save and return to printing mode.

Printer language	Emulation	HP4.
Tray select	Manual	Off, On
	Paper In	Tray 1, tray 2, Front Tray Envelope, Feeder
	Auto Tray (if tray 2 installed)	Off, On
Edit size	Edt size	Cassett, Letter, Exec, Legal 14, Legal 13. A4, A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., C4 Envelope
Paper Size	Manual	Letter, Exec, Legal 14, Legal 13. A4, A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., C4 Env.
	Feeder (if installed)	A4, A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
Media Type	Tray 1/ 2	Medium, M Heavy, Heavy, Light, M Light.
	Manual	Medium, M Heavy, Heavy, Light, M Light.
	Feeder	Medium, M Heavy, Heavy, Light, M Light.
Paper Size Check	Size Chk	Enable, Disable
Copies	Copies	1 to 99
Fonts and Symbols	Font Src (Source)	Resident, Card,(if installed) DII Soft (if loaded)
	Font No.	I000, C000, S0001
	Font Pitch (if scaleable)	10.00, 0.44to 99.99
	Font Height (if scaleable)	12.00, 4.00 to 999.75
	Symbol (Symbol set)	Roman-8, PC-8, PC-850, IBM-437, IBM-850 Plus many others.
Page Layout 1	A4 Width	78 col., 80 col.
	White Page Skip (Blankskip)	Off, On
Page Layout 2	Orient	Prtrt, Landscp
	Lines/Pg	64 Lines 5 to 128
Host I/F	Host I/f	Auto I/F Parall, RS232C

1200ex – Level - 2 Menu List

Print Mode	Mode (resolution)	600, 300
	Smoothing	On, Off
Memory Usage	RAST Buf	Auto, 180kb to 3.96 Mb, Ful Ltr, Ful A4, Ful Lgl
	Rec. Buf	Auto,8Kb to 1Mb
	Font Prot	Auto, Off, 100Kb to 1.4MB
	Free Mem	Displayed in Kb
Auto Operation	Autocont	Off, On
	Autoeject	Off, On, 5 Secs to 300Secs
Darkness Control	Darkness	0, +1, +2, -2, -1.
Power Saving	Pwr Save	Enable, Disable
Low Toner	Low Tnr	On, Off
Toner Saving	Toner	On, Off
Clearable Warnings	CLEARABL WARNINGS	On, Job
Parallel I/F	High Speed	On, Off
	BI-Direct	Enable, Disable
	I-Prime	Off, On
RS232/C	Flow Ctl	DTR High, DTR Lo, XON/XOFF, RBST XON
	Baud Rate	9600, 300, 600, 1200, 2400, 4800, 19200.
	Data Bits	8-Bits, 7-Bits
	Parity	None, Even, Odd.
	Min. Busy	200 mS, 1 S
Language	Language	English, German, French, Italian, plus others.