

OL400e/410ex - Level -1 Menu List

- To enter the MENU set-up, please ensure the printer is off-line and then briefly depress the MENU button.
- To enter level 2, please ensure the printer is off-line and then hold the MENU button for 2 seconds.
- Move through the MENU button and when your wish to change an option press ENTER and then the **+** or **-** or the **< >** keys. Press Enter to set.
- When you have finished with the MENU set-up press ONLINE to save and return to printing mode.

Printer language	Emulation (only if optional board fitted)	HP II-P
Tray select	Paper in	Tray, Manual
Paper size	Tray	A4, A5, A6, B5, FREE, Letter, Exec, Legal 14, Legal 13
	Manual	A4, A5, A6, B5, FREE, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
Copies	Copies	1 to 99
Fonts and Symbols	Font Src (Source)	Resident, Card, DLLsoft
	Font No.	1000 (Internal), C000 (Card), S001 (Downloaded).
	Symbol (Symbol set)	Roman-8, PC-8, PC-850, IBM-437, IBM-850 Plus many others.
	HP Cart.	None, B, F
Page Layout	Orient (Orientation)	Portrait, Landscap
	Lines/Pg	64, 5...128 Lines
	A4 Width	78 col., 80 col.
	Blnskp (Blankskip)	Off, On
Host I/F	Host I/F	Auto I/F, Parall, RS232C.

Level -2 Menu List

Allocate Memory	Page Prot	Off, Letter, Legal, A4
	Rec Buf	8Kb, 20 Kb, 50Kb, 100Kb, 1Mb
Auto Operation	Autocont	Off, On
	Autoeject	Off, On
Darkness Control	Darkness	0, +1, +2, -2, -1.
Power Saving	Pwr Save	Enable, Disable
Parallel I/F	I-Prime	Off, On
RS232/C	Flow Ctl	DTR High, DTR Lo, XON/XOFF, RBST XON
	Baud Rate	9600, 300, 600, 1200, 2400, 4800, 19200.
	Data Bits	8-Bits, 7-Bits
	Parity	None, Even, Odd.
	Min. Busy	200 mS, 1 S