

## OL 6e-6ex – Level 1 Menu List

- To enter the MENU set-up, please ensure the printer is off-line and then briefly depress the MENU button.
- To enter level 2, please ensure the printer is off-line and then hold the MENU button for 2 seconds.
- Move through the MENU button and when your wish to change an option press ENTER and then the **+** or **-** or the **<** **>** keys. Press Enter to set.
- When you have finished with the MENU set-up press ONLINE to save and return to printing mode.

<b>Printer language</b>	Emulation	<b>HP4</b> , Epson FX, IBM PPR, Hiper-W, Auto
<b>Tray select</b>	Manual	<b>Off</b> ,
	Paper In	<b>Tray 1</b> , tray 2, ( if installed)
	Auto Tray ( if tray 2 installed)	<b>Off</b> , On
<b>Edit size</b>	Edt size	<b>Cassette</b> , Letter, Exec, Legal 14, Legal 13. <b>A4</b> , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Custom
<b>Paper size</b>	Tray	<b>A4</b> , A5, A6, B5, Letter, Exec, Legal 14, Legal 13 (optional tray fitted)
	Manual	<b>A4</b> , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
	Tray 2 ( if installed)	<b>A4</b> , A5, A6, B5, Letter, Exec, Legal 14, Legal 13
	Feeder ( if installed)	<b>A4</b> , A5, A6, B5, Com-9, Com-10, Monarch, DL Env., C5 Env., Letter, Exec, Legal 14, Legal 13.
<b>Media Type</b>	Tray 1/ 2	<b>Medium</b> , M Heavy, Heavy, Light, M Light.
	Manual	<b>Medium</b> , M Heavy, Heavy, Light, M Light.
<b>Paper Size Check</b>	Size Chk	<b>Enable</b> , Disable
<b>Copies</b>	Copies	<b>1</b> to 99
<b>Fonts and Symbols</b>	Font Src (Source)	<b>Resident</b> , Card,( if installed)
	DII Soft ( if loaded)	
	Font No.	<b>1000</b> to 1047
	Font CPI ( if scaleable)	<b>10.00</b> , 0.44to 99.99
	Font HGT( if scaleable)	<b>12.00</b> , 4.00 to 999.75
	Symbol (Symbol set)	<b>Roman-8</b> , PC-8, PC-850, IBM-437, IBM-850 Plus many others.
	Symbol	<b>Roman-8</b> , (81 sets available)
<b>Page Layout 1</b>	A4 Width	<b>78</b> col., 80 col.
	Blnkskp (Blankskip)	<b>Off</b> , On
	CR Function	<b>CR</b> , CR+LF
	LF Function	<b>LF</b> , LF+CR

## Level -2 Menu List

<b>Print Mode</b>	Mode (resolution)	<b>600</b> , V1200 (600x1200), 300
<b>Memory Usage</b>	RST Buffer	V1200 – <b>Auto</b> , 480kb to 1.44 Mb
		600 – <b>Auto</b> , 360 kb to 1.44Mb
		300 – <b>Auto</b> , 180kb to 900 kb, Ful Ltr, Ful A4, Ful Lgl
	Receive Buffer	<b>Auto</b> ,8Kb to 1Mb
	Font Prot	<b>Auto</b> , Off, 100Kb to 1.1MB
	Free Mem	<b>##### Kb</b>
<b>Auto Operation</b>	Autocont	<b>Off</b> , On
	Auto Eject	<b>Off</b> , On, 5 Secs to 300Secs
<b>Darkness Control</b>	Darkness	<b>0</b> , +1, +2, -2, -1.
<b>Power Saving</b>	Pwr Save	<b>0 Sec</b> , 8 Min Disable
<b>Low Toner</b>	Low Toner	<b>On</b> , Off
<b>Toner Saving</b>	Toner	<b>Disable</b> , Medium, Light
<b>Parallel I/F</b>	Speed	<b>High</b> , Medium
	BI-Direct	<b>Enable</b> , Disable
	I-Prime	<b>Off</b> , On
<b>Language</b>	Language	<b>English</b> , German, French, Italian, plus others.